

FEATURE UPDATE

Version 191 Date Code Update

Effective July 22nd, 2019, all XR Series panels are manufactured with updated Version 191 (7/2/19) firmware.

Features

736V Support

Updated Version 191 supports the new 736V V-Plex module, which allows technicians to program V-Plex Devices into XR Series panels.

Setting the 736V Address

1. Navigate to **DEVICE SETUP**.
2. At **DEVICE NO**, enter the device number of the LX-Bus™ slot taken up by the module.
3. If the LX-Bus already has zone programmed, **ZONES PROGRAMMED CONTINUE? NO YES** displays. To continue programming, select **YES**.
4. At **DEVICE NAME**, enter a name for the module.
5. (XR550 only) At **DEVICE TYPE**, select **VPX**.

Programming V-Plex Zones

1. Navigate to **ZONE INFORMATION**
2. At **ZONE NO**, enter the device zone that corresponds to the LX-Bus.
3. At ***UNUSED***, enter the zone name.
4. At **ZONE TYPE**, select the zone type.
5. At the Area Assignment section, select the area.
6. At the **NEXT ZN?** prompt, select **YES**.
7. At the **DMP WLS? NO YES** prompt, select **NO**.
8. At **VPLEX DEVICE SERIAL #**, enter **A** followed by the 7-digit serial number.
9. At the **NEXT ZN?** prompt, select **YES**.
10. Repeat steps 2 through 10 for any remaining devices.
11. To save panel programming, navigate to **STOP** and press **CMD**.

1134 Speed-up

Updated Version 191 improves the panel response to the 1134 by increasing the priority of the unlock message.

Obtaining the New Firmware

XR Series firmware updates are available, free of charge, at DMPDealerAdmin.com or DMP.com/Dealer_Direct