

TECHNICAL UPDATE

Version 702 (9/22/20) Date Code Update

Effective October 12th, 2020, all XR150INT/XR550INT Series Panels are being manufactured with updated Version 702 (9/22/20) firmware.

Updated Functionality

Tamper CID Messages

Previously, the panel sometimes transmitted an incorrect CID message when the zone reported a tamper message on Night, Day, Exit, and Instant zones. This issue is resolved by this date code release. Refer to the table below. The red text indicates the new messages that are being sent in Version 702 (9/22/20).

Alarm Action	Condition	Communication			
		CID	DMP Serial 3	Push	Keypad Display
DO - None	Loop Open	1 144	Zi	TAMPER	-Tamper
DS - None	Loop Short	1 144	Zi	TAMPER	-TAMPER
AO - Alarm	Loop Open	1 130, 1 144 (both)	Za/Zi (both)	Burg Alarm TAMPER (both)	Zone Alarm -TAMPER (kpd red)
AS - Alarm	Loop Short	1 130, 1 144 (both)	Za/Zi (both)	Burg Alarm TAMPER (both)	Zone Alarm -TAMPER (kpd red)
DO - None	Zone Open	None	None	None	Zone Fault
AO - Alarm	Zone Open	1 130	Za	Burg Alarm	Zone Alarm

Bypass CID Messages

Updated Version 702 firmware now sends correct CID messages for Bypass on Night, Day, Exit, and Instant zones types.

Previous message examples appeared as:

- Night Zone - Restore - 3 370 (Protection Loop)
- Instant Zone - Restore - 1 110 (Fire Alarm)

Updated Version 702 message examples appear as:

- Night Zone - Restore - 3 570
- Instant Zone - Restore - 3 570

Removed Tamper Option

Updated Version 702 has removed the tamper option for Arming Zone types.

Obtaining the new Software

Version 702 (9/22/20) firmware is now available for download at [DMP.com/Dealer_Direct](https://www.dmp.com/dealer-direct).