



# Thinline™ Series Icon Keypads



## FEATURES

- ▶ Visual and audible alarm notification
- ▶ Easy-to-use shortcut key operation
- ▶ Optional integrated proximity reader
- ▶ Silence alarm while system remains armed
- ▶ For use with the XT Series™ Panels

### ENHANCED OPTIONS

- ▶ 7363 keypad proximity reader built-in

- ▶ Affordable solution for both residential and small commercial operations
- ▶ Attractive Thinline keypad housing
- ▶ Display icons provide quick, intuitive, and easy-to-use visual reference for panel operation
- ▶ False Alarm features supported
- ▶ Extend schedules with the touch of a button
- ▶ Keypad and logo backlighting turn Red in alarm conditions
- ▶ User-adjustable brightness, tone, and volume controls
- ▶ Three two-button panic alarms for panic, emergency and fire
- ▶ Optional on-board proximity reader allows users to present proximity credentials to arm or disarm the system
- ▶ Simple harness connection to 4-wire keypad bus
- ▶ Distinct fire, burglary, zone monitor, and prewarn tones
- ▶ Displays system status
- ▶ Optional backboxes for conduit or wall-mount applications



### SIMPLE TO USE

The easy-to-understand icons, combined with the three-character display, provide visual feedback that enables simple arming, disarming, and other functions.

The User Menu allows you to quickly browse through menu options.

Disarming and Arming functions are fast and easy. Any function allowed by the user authority level is simply accessed through the keypad, such as silencing alarms, resetting sensors, or displaying events.

### CODELESS ARMING AND DISARMING

The innovative 7363 Thinline Series Icon keypads contain an on-board DMP proximity reader that allows users to simply present their proximity credential to the keypad to arm or disarm the system.

### USER-FRIENDLY SHORTCUT KEYS

One-button shortcut keys provide quick, easy access to a variety of common functions. Holding down a keypad button for two seconds until the tone resounds provides confirmation. For example, pressing the Instant Key (INST CMD) during the exit delay countdown instantly arms the system. Users can arm, monitor zones, easy exit, test, reset the system, add users, instant arm and a variety of other functions.



Shortcut Keys

### FALSE ALARM FEATURES

Providing end users with a way to reduce false alarms, both Cancel/Verify™ and the False Alarm Question features prompt end users to validate whether an alarm has occurred after entering their code. In a Home/Sleep/Away or All/Perimeter system, the user can manually confirm a valid burglar alarm and an alarm is then sent to the Central Station.

### EXTEND A SCHEDULE

When the programmed open period is about to expire, the schedule can be easily extended for an additional one to nine hours by entering your user code or presenting a proximity credential.

### TWO-BUTTON PANIC KEYS

The top row of keys can be used as two-button panic keys. The user simply presses and holds two of the keys simultaneously to send either a panic, non-medical emergency, or fire report to the Central Station.

### VALUABLE VISUAL ALARM INDICATOR

In a normal state, both the keypad and logo backlighting remain Green. However, during an alarm state, the keypad and logo turn Red. The change in color allows users to instantly recognize an alarm condition.



Red Backlighting



Green Backlighting

### USER CONTROL

User options allow for adjusting brightness, speaker tone, and volume. The panel brightness automatically adjusts to maximum for easy viewing when any key is pressed, then resets to the user-specified brightness level.

### DISTINCT SOUND PATTERNS

The keypads also provide distinct sound patterns for fire, burglary, zone monitor, and prewarn, giving users an audible alert of the type of event occurring.

### KEYPAD SUCCESS FEEDBACK

After correctly changing a system setting using the keypad, the user hears a one-second confirmation beep. If the user makes an error or the operation is unsuccessful, the user hears a four-beep warning tone.

### VERSATILE UNSUPERVISED OPERATION

Unsupervised operation allows installation of an unlimited number of keypads using the same device address. Increasing the number of keypads allows maximum system operating flexibility.

### RETROFIT ANY EXISTING DMP SYSTEM

Retrofitting is quick and easy. Thinline Series Icon keypads have the same footprint as existing DMP keypads and mount in currently installed backboxes. No special modules are required. A simple panel EPROM upgrade is all that is needed for the Thinline Series Icon keypads to operate. Create a new look and provide greater functionality for an existing system at just a fraction of the cost of all new equipment.

### MULTIPLE-KEYPAD SAVINGS

Install multiple keypads on the same wire run. Compatibility and cost savings make the Thinline Series Icon an asset in every installation.

## PRIVATE LABELING

DMP offers dealers the option to present their company logo on the keypad's rubber logo insert, replacing the DMP logo. The backlighted logo glows green during normal operation and turns Red in an alarm state.



## FIXED ICONS

Easy-to-use intuitive icons and user messages provide for simple operation and quick status confirmation.

	AC Power Status		System Ready to Arm
	Battery Status		System Not Ready to Arm
	System is Disarmed		Burglar Alarm
	Some or all areas are armed		Fire Alarm
	Some or all areas armed Instant	<b>BYPASS</b>	Bypass Faulted Zones
	Door and window zones selected for chime	<b>EXTEND</b>	Extend Schedule
	Failed Dialer Status	<b>CANCEL</b>	Cancel Alarm
	Network Communication Status	<b>VERIFY</b>	Verify Alarm

## COMPATIBILITY REFERENCE SHEET

### KEYPAD MODEL FEATURES

Model	Two-Button Panic	Red in Alarm	Internal Prox Reader
7360	•	•	
7363	•	•	•

### ACCESSORIES

#### Backboxes

695	Keypad Conduit Backbox
696	Keypad Backbox

#### Keypad Wiring Harness

300	4-wire harness
-----	----------------

#### HID Proximity Credentials

1306	Prox Patch™
1306PW	Prox Patch™
1326	ProxCard II® Card
1346	ProxKey II® Access Device
1386	ISOProx II® Card

#### Farpointe Proximity Credentials

CSR-35P	Conekt Bluetooth Reader
Delta 3	Contactless Mullion-Mount Smartcard Reader
Delta 5	Contactless Mullion-Mount Smartcard Reader
Delta 6.4	Contactless Smartcard Reader and Keypad
P-300-H-A	Cascade Proximity Reader
P-500-H-A	Alps Proximity Reader
P-620-H-A	Denali Proximity Reader with Keypad
P-640-H-A	Patagonia Proximity Reader with Keypad

### SPECIFICATIONS

Operating Voltage	12 VDC
Dimensions	7" W × 5.25" H × 0.5"D
Display Type	Fixed Icon LCD
Color	White

### CURRENT DRAW

7360 Standby	60 mA
Alarm	67 mA
7363 Standby	73 mA
Alarm	80 mA

### COMPATIBILITY

7300 Thinline Series Icon keypads are compatible with DMP XT Series Panels.

### CERTIFICATIONS

California State Fire Marshall (CSFM)  
ETL: 3139201NYM  
ANSI/SIA CP-01 False Alarm Reduction  
ANSI/UL 1610 Central Station Burglar  
ANSI/UL 609 Local Burglar  
ANSI/UL 1076 Proprietary Burglar  
ANSI/UL 365 Police Connected Burglar  
ANSI/UL 1023 Household Burglar  
ANSI/UL 985 Household Fire Warning

FCC Part 15 ID: CCKPC0086  
Industry Canada ID: 5251A-PC0086

For additional information, access [www.DMP.com/Compliance](http://www.DMP.com/Compliance).



7360-W | 7363-W



THIN-ICON-B/10 (Black) | THIN-ICON-W/10 (White) | THIN-ICON-I/10 (Ivory)

800-641-4282 | [DMP.com](http://DMP.com)  
2500 N. Partnership Blvd, Springfield, MO 65803  
Designed, engineered & manufactured in Springfield, MO  
using U.S. & global components

**LIMITED WARRANTY:** DMP warrants that the products manufactured by DMP and described herein shall be free from defects of manufacture, labeling, and packaging for a period of three (3) years from the invoice date to the original Buyer, provided that representative samples of the defective products are returned to DMP for inspection...To read the full DMP Limited Warranty, go to [DMP.com/Warranty](http://DMP.com/Warranty) or check the DMP Price List or Catalog.