XTLC/XTLN

August 2015

Version 123 Firmware Update

XTLC/XTLN Version 123 (8/27/15) firmware is now available for download on the DMP Dealer Direct Website at http://dmp.com/dealer.

Effective September 1, 2015, all XTLC/XTLN panels will be manufactured and shipped with updated Version 123 (8/27/15) firmware.

Fast Program Option

A new FAST PROGRAM option has been added to the Programming Menu to allow complete panel programming using only essential programming options. When the panel programming defaults are acceptable for installation and only basic programming options are needed, FAST PROGRAM allows the installer to quickly enter information without navigating all of the programming menus. The new FAST PROGRAM option has been added immediately after the INITIALIZATION and before the COMMUNICATION programming option. The new one page Fast Programming Sheet is included in this feature update.

FAST PROGRAM

FAST PROGRAM

The Fast Program section allows you to quickly configure the essential settings for XTLC/XTLN control panels. When the panel programming defaults are acceptable for installation and only basic programming options are needed, FAST PROGRAM allows the installer to quickly enter information without navigating all of the programming menus. After choosing FAST PROGRAM, continue programming the basic list of options:

- Account Number
- First IP Address
- App Key (XTLN only)
- System (Area, A/P, or H/S/A)
- Hours from GMT
- Weather Zip Code
- Alarm Sounder 1 Serial # (Output 41)
- Zone Wireless Serial Number(s)

Once all wireless zone serial numbers have been programmed, press the back arrow to display FAST PROGRAM. Press COMMAND and STOP is displayed. Press any Select key to save and exit the programming menu.

Note: All standard programming options are still available in the programming menu.

Fast XTLC and XTLN Programming Sheet

New Fast XTLC and XTLN Programming Sheets are also included with each panel and contain only the fast programming sections for a quick and easy installation.

Fast XTLC Programming Sheet LT-1095F

Fast XTLN Programming Sheet LT-1238F

Note: The XTLC and XTLN Programming Sheets and Programming Guides provide the default information (BOLDED) for each control panel and descriptions for each programming step.

XTLC Programming Sheet LT-1095

XTLC Programming Guide LT-1108

XTLN Programming Sheet LT-1238

XTLN Programming Guide LT-1221

Output Setup

The Output Information programming option has been renamed to Output Setup.

Obtaining the New Software

XTLC/XTLN Series software updates are available for download free of charge on the DMP Dealer Direct Website at http://dmp.com/dealer.



FEATURE UPDATE

FAST XTL PROGRAMMING SHEET

Name		Account Number	Date	
Address		_ City	_ State	_Zip
Communication Account Number	(1 to 65,535 default = 12345)			
First IP Address				
System Options System Hours from GMT Weather Zip Code	AREA A/P H/S/A (0 to 23 hrs., default = 6) Default = 0			
Output Setup Output 41 Serial #	ALARM SOUNDER 1			
Note: Bell Output au	itomatically set to Output 41.			

Zone Information

Zone #	Zone Name	Zone Type	Area	Serial Number
1	FRONT DOOR	EX	PERIM	
2	BACK DOOR	EX	PERIM	
3	INTERIOR DOOR	NT	INT	
4	UPSTAIRS DOOR	EX	PERIM	
5	BASEMENT DOOR	EX	PERIM	
6	GARAGE DOOR	EX	PERIM	
7	WAREHOUSE DOOR	EX	PERIM	
8	SHIPPING DOOR	EX	PERIM	
9	BREAKROOM DOOR	NT	INT	
10	STOCKROOM DOOR	NT	INT	
11	FRONT MOTION	NT	INT	
12	BACK MOTION	NT	INT	
13	INTERIOR MOTION	NT	INT	
14	UPSTAIRS MOTION	NT	INT	
15	BASEMENT MOTION	NT	INT	
16	GARAGE MOTION	NT	INT	
17	GLASS BREAK	NT	INT	
18	WATER DETECTOR	AUX 1	INT	
19	LOW TEMPERATURE	AUX 1	INT	
20	SMOKE DETECTOR	FI		
21	FRONT SMOKE	FI		
22	BACK SMOKE	FI		
23	INTERIOR SMOKE	FI		
24	UPSTAIRS SMOKE	FI		
25	BASEMENT SMOKE	FI		
26	GARAGE SMOKE	FI		
27	WAREHOUSE SMOKE	FI		
28	SHIPPING SMOKE	FI		

TU-0814 © 2015 Digital Monitoring Products, Inc.

