

Updated Supporting Products

- ▶ [DMPDealerAdmin.com](#)
Version 2.11
- ▶ Tech APP
Version 2.1
- ▶ Remote Link
Version 1.87

Features

- ▶ XR panel Z-Wave Plus Operation
- ▶ Z-Wave Backup and Restore
- ▶ Dual Authority
- ▶ 50 Sensor Activity Zones

Z-Wave Plus Operation

With XR Version 182, Z-Wave Plus devices will see an increase in speed, improved network reliability, and an increased distance between devices. Additionally, you can now initialize Z-Wave devices, as well as check the hardware type and firmware level, from the **Diagnostics Menu**.

This update also allows you to perform a Z-Wave Backup and Restore from Dealer Admin or Remote Link.

Dual Authority

-  In **Area Information**, the option for programming the Two-Man Rule has been updated to Dual Authority. Your options for Dual Authority are **NONE, ARM, DISARM**, and **ALL**. Keep in mind, if **DISARM** is chosen, Dual Authority is required for both Disarm and Access Control.
- In the **Profiles Menu**, users are given the option to enable Dual Authority on certain profiles. This gives users the ability to choose which profiles require Dual Authority based on what is programmed in Area Information. [DMPDealerAdmin.com](#) and Remote Link now give you the option to use the Dual Authority feature.

[DMPDealerAdmin.com](#)

1. Log into [DMPDealerAdmin.com](#).
2. Select a system and click Full Programming. Select **Area Information**.
3. Once an area is selected, users can then enable the Dual Authority option.

Additional Sensor Activity Zones

Before XR Version 182, users could only receive reports from up to 10 night or exit type zones when activity would occur on their system.

With XR Version 182, when enabled at [DMPDealerAdmin.com](#) or in the Tech APP, Virtual Keypad App users now have the ability to allow up to 50 night or exit type zones to report to them as activity occurs on their system. Follow the steps below to enable this feature in [DMPDealerAdmin.com](#) and on the Tech APP.

[DMPDealerAdmin.com](#)

1. Log into [DMPDealerAdmin.com](#).
2. Select a system and click **Edit** to edit the system information page.
3. In the **Sensor Activity** section, enable up to 50 sensors for the user to view.

Obtaining the New Software and Firmware

If you updated to XR 182 (8/31/18), please update to XR 182 (9/11/18) to ensure proper clearing of a tamper trouble when using a device programmed at address 16. This only affects keypad device 16, if programmed. If you are not using keypad number 16, there is no need to update. This issue does not affect XR150 panels. Firmware updates are available, free of charge, at [DMP.com/Dealer_Direct](#). Effective October 18th, 2018, XR150/XR550 Series panels will be manufactured with Version 182 (9/11/18) firmware.

Tech APP updates are available for download, free of charge.