

FEATURE UPDATE | FEBRUARY 2021

Version 8.8 (1/29/21) Update

Effective February 3, 2021, all Entré Security & Access Management software will be manufactured as Version 8.8 (1/29/21).

Entré 8.8 works with panel firmware Versions 181 to 202.

Features

202/702 Support

Entré 8.8 supports and comes bundled with XR Series Version 202 firmware. The features of this version include:

Card+Pin By Area

For greater customization of DMP's access control system, the XR550 panel allows the Card + Pin feature to be assigned not only to selected profiles, but also to selected areas. This option gives customers the added flexibility and security to require Card + Pin only in certain areas and only for selected profiles. If Card + Pin isn't enabled in that profile for other areas, it won't be required. Enable **Card plus pin** in **Edit - Area > Area**.

Private Door Programming

Enable **Private door** between **Device communication type** and **Access areas** in Device Setup. Enabling this option will disable **Access areas** and **Egress areas**. Up to four Private Doors can be assigned to a profile.

For more information about these features, [see the XR Series Version 202 Technical Update](#).

Mapping in Web Client

The Entré Web Client has the same functionality as the Entré Client to set up, add, edit, and delete in the **Map Editor** module.

Video Analytics Message Support

Enabling Video Reports will allow the panel to send video system reports to Entré when an OpenEye® event message has been received from a camera. Enable System Video reports in **Edit - Panel > System Reports**. Also enable Video Reports in **Edit - Panel > Remote Options > Entre and Integrator**.

1108 Doorbell Support

Entré 8.8 supports the 1108 Doorbell module.

Remotely Triggered Virtual Keypad App Panics

Entré 8.8 supports Virtual Keypad App panics that are triggered remotely. Now customers can utilize Virtual Keypad App to send panics remotely and view them in the event history. There are additional improvements to the way the keypad panics are displayed in the event history.

Add Panel from Side Menu

In this NOC feature, select **New Panel** from the side menu to add a panel.

Improvements

Log Codes

Log codes are now more descriptive so users can troubleshoot issues faster.

Panel Version in Hardware List

The **Hardware List** displays the panel's version. This column can be added, removed, and searched. Default displays the column.

Entré Migration Tool

The migration tool is now compatible with XR Series panels with versions 201, 202, and 702.

Obtaining the New Software

Entré Security & Access Management software Version 8.8 is provided to dealers who have previously purchased an Entré license, are current with their Entré support agreement, and who have an Entré Certified Technician.

To upgrade to Entré Version 8.8 (1/29/21), please complete the [Pre-Upgrade Checklist \(LT-1782\)](#) before contacting the Software Support Team in DMP Technical Support at 888.436.7832.

For more information about Entré, visit DMP.com/Entre.