

XT30/XT50 and XTL Series Control Panels

August 2014

Version 119 Software Update

The XT30/XT50 and XTL Series Version 119 (7/30/14) software is now available for download on the DMP Dealer Direct Website at <http://dmp.com/dealer>.

Effective August 18, 2014, all XT30/XT50 and XTL Series panels will be manufactured with updated Version 119 (7/30/14) software. As of September 30, 2014, inventory for the XT30/XT50 and XTL panels will be completely updated to Version 119 (7/30/14) software.

Features

False Alarm Question

When a burglar alarm occurs in an area system and a user code is entered at a keypad Status List, keypads now display IS THIS A FALSE ALARM? NO YES or CANCEL VERIFY. Selecting NO or Verify sends an alarm message to the Central Station. Selecting YES or CANCEL sends an alarm cancelled message to the Central Station and disarms the areas that the user has the authority to disarm. The Use False Alarm Question appears in the System Options programming menu just after Occupied Premises and was previously only available for All/Perimeter and Home/Away Systems.

USE FALSE ALARM QUESTION NO YES

Use False Alarm Question

Select YES to display IS THIS A FALSE ALARM? NO YES at the keypad when a burglar alarm occurs. Select NO to display CANCEL VERIFY. Default is YES.

My Access Alarm Cancel

When a burglar alarm text message is received from an area system, My Access users may now reply with "cancel" in a text message to the panel to cancel the alarm.

Energy Metering Light Modules

XT30/XT50 Series Control Panels now support Z-Wave Light modules with energy metering capabilities. In the Lights screen of the 7800 Series Graphic Keypads operating with Version 104 (3/9/14) software, the icon for the energy metering module displays the current power usage of the connected device in Watts (W) and below the accumulated usage in kilowatt-hours (kWh). Pressing RESET returns the accumulated usage counter to 0.

For more information on this feature refer to 7800 Series Graphic Keypad Version 104 (3/9/14) software Technical Update (TU-0728).

Battery Supervision

The 1100 Series wireless receiver, either built-in to the XT50, or an external 1100D, 1100DH or 1100DI will now add an additional method to detect low battery from a wireless transmitter. A low battery has always been communicated from DMP 1100 Series transmitters on any communication from that transmitter. This could be during check-in, alarm, trouble or restoral. A new feature is being added to cause an 1100 Series transmitter to send a battery status periodically, even if the transmitter is not programmed for check-in. This will improve low battery detection for devices that may have a supervision time of zero.

Updated Operation

Push Notifications

Previously, Push Notifications were not sent when Communication Type was set to CID or DD in panel programming and Backup Cellular was set to YES.

Push Notifications are now sent using CELL communication if Communication Type is set to CID, DD or CELL. If Communication Type is set to NET, Push Notifications are sent using NET.

Zone Monitor

Occasionally, when the 5 Key (CHIME) was pressed and held on a keypad to enable Zone Monitor, the keypad did not annunciate the door chime sound to indicate the Zone Monitor was enabled. The Zone Monitor feature operated normally afterwards. The chime sound now always annunciates Zone Monitor is enabled.

Account Number

For the following issue to occur **ALL** of the actions below were required.

1. EasyNet communication was programmed for the account at vk.securecomwireless.com, and
2. The panel had been reset (power cycled or J16), and
3. An **INVALID** user code was the **FIRST** code entered using the Virtual Keypad App or Browser

When all of the actions above occurred, on rare occasion, the panel's account number could have changed to 0.

This issue could **NOT** occur when the **FIRST** user code entered after a panel reset was a **VALID** user code. Afterwards, another panel reset was required before the issue would have been able to occur.

Obtaining the New Software

XT30/XT50 and XTL Series software updates are available for download free of charge on the DMP Dealer Direct Website at <http://dmp.com/dealer>.