

FEATURE UPDATE | APRIL 2025

Version 252 Update

Updated Version 252 (3/5/25) firmware is now available for XT75 Control Panels.

Time Change

This update allows the panel to receive time updates from SecureCom Wireless® Servers. This option can be enabled in panel programming on the keypad or on Dealer Admin. To receive time updates from SecureCom Wireless Servers, complete the following steps:

1. At the keypad, enter **6653** (PROG) and select **CMD** to enter the programming menu.
2. In **SYSTEM OPTIONS**, go to **REQUEST TIME CHG** and select one of the following options:
 - **NO** — Do not request time update
 - **SCS** — Request time update from the monitoring center receiver
 - **SCW** — Request time update from SecureCom Wireless
3. In **DST**, select **YES** to observe daylight saving time. This option is only available if you selected **SCW**.

Zone Location

This update allows you to assign zones an optional secondary name to give further clarification on the location of a zone. Zone Location provides the monitoring center additional support and promotes quicker response times from monitoring center operators and first responders. The secondary name is only visible to the monitoring center and does not display on the keypad.

This option can be enabled in panel programming on the keypad or on Dealer Admin. To add a Zone Location to a zone, complete the following steps:

1. At the keypad, enter **6653** (PROG) and select **CMD** to enter the programming menu.
2. In **Zone Information**, enter the **Zone Number** and **Zone Name**, then proceed to the next prompt.
3. The **Zone Location** prompt appears after **Zone Name**. Press any select key or area and then enter up to 32 characters for the zone location. This prompt can also remain blank, and the zone name is sent to the Monitoring Center instead.
4. Press **CMD** to continue.

Sempro Communication

Previously, systems without a programmed communication path could not send messages to SecureCom Wireless servers. Now, systems communicating with Dealer Admin send messages regardless if they have a communication path programmed, allowing for push notifications and analytics in Dealer Admin and Virtual Keypad.

Integrator Connection

An integrator path has been added to support integration with DMP systems. This integrator path creates a dedicated communication channel on the security panel that allows security integrators to connect and configure the system without taking up a port that is already being used for other functions, like communicating to a monitoring center.

Obtaining the New Firmware

XT75 firmware updates are available, free of charge, on Dealer Admin (dealer.securecomwireless.com).