

Version 183 Firmware Update

Version 183 (11/28/18) firmware is now available on DMPDealerAdmin.com or for download at DMP.com/Dealer_Direct.

Effective December 31st, 2018, all XT Series panels will be manufactured with Version 183 firmware. The following features are available:

Features

⊕ Carbon Monoxide (CO) Zone Type and Temporal 4 Bell Cadence

With Version 183, carbon monoxide detectors have a designated Carbon Monoxide (CO) zone type in **Zone Information**. For a CO Zone Type, the default bell cadence is **Temporal 4**, which can be programmed in **Bell Options**.

⊕ Wireless Encryption and Passphrase Support

Version 183 now supports wireless encryption, allowing the panel to communicate with 1100E Series wireless devices version 200 and higher. This feature allows you to use both encrypted and older, unencrypted wireless devices simultaneously.

In **System Options**, choose from three encryption support settings. Select **ALL** if you are using only encrypted wireless devices. Select **BOTH** if you are using both encrypted and unencrypted wireless devices at the same time. Select **NONE** if you are not using encrypted wireless devices.

If you select ALL or BOTH, you will be prompted to enter an 8-digit hexadecimal **Passphrase**.

DMPDealerAdmin.com

1. Navigate to **Full Programming**.
2. Select **System Options**.
3. Enable **Wireless Encryption** (**ALL** or **BOTH**).
4. Create a **Passphrase**.

Remote Link

1. Navigate to **Panel Programming**.
2. Select **System Options**.
3. Enable **Wireless Encryption** (**ALL** or **BOTH**).
4. Create a **Passphrase**.

⊕ 738T Support of XTLplus and XTLtouch

With Version 183, the XTLplus (Rev 6 PCB, Level 102 and higher) and XTLtouch now support the 738T. This allows you to take over Honeywell, Interlogix, or 2GIG wireless transmitters without replacing the wireless sensors.

⬆ Improved Push Notifications

Push notifications will now be sent over the backup path in the event of a primary path failure. For example, if you have a network and cellular panel and the network goes down, notifications will be sent over cellular.

Supporting Software Updates

- Dealer Admin Version 2.15 - Dealer Admin now supports the new CO Zone Type and Temporal 4 bell cadence, as well as wireless encryption.
- Remote Link Version 1.88 - Remote Link Version 1.88 supports the new CO Zone Type and Temporal 4 bell cadence, as well as wireless encryption. The update is available for free at DMP.com/Dealer_Direct.
- SCS-150 and SCS-VR Support - SCS-150 Version 106 and SCS-VR Version 1.4.4 supports the updated CO Zone message type. Contact the Software Support Team in DMP Technical Support at 1.888.436.7832 for information on updating SCS-150 Version 106 and SCS-VR Version 1.4.4.

Obtaining the New and Firmware

XT Series firmware updates are available, free of charge, at DMPDealerAdmin.com or DMP.com/Dealer_Direct.