

Version 711 Update

Version 711 (1/21/21) firmware is now available on Dealer Admin (dealer.securecomwireless.com) or for download at DMP.com/Dealer_Direct.

Effective February 8th, 2021, all XT International Series Panels are being manufactured with Version 711 firmware.

Panel Features

Tamper CID Messages

Previously, the panel sometimes transmitted an incorrect CID message when the zone reported a tamper message on Night, Day, Exit, and Instant zones. This issue is resolved by this firmware release. Refer to the table below. The red text indicates the new messages that are being sent in Version 711 (1/21/21).

Alarm Action	Condition	Communication			
		CID	DMP Serial 3	Push	Keypad
DO - None	Loop Open	1 144	Zi	TAMPER	-TAMPER
DS - None	Loop Short	1 144	Zi	TAMPER	-TAMPER
AO - Alarm	Loop Open	1 130, 1 144 (Both)	Za/Zi (Both)	Burg Alarm TAMPER (Both)	Zone Alarm -TAMPER (KPD RED)
AS - Alarm	Loop Short	1 130, 1 144 (Both)	Za/Zi (Both)	Burg Alarm TAMPER (Both)	Zone Alarm -TAMPER (KPD RED)
DO - None	Zone Open	None	None	None	Zone Fault
AO - Alarm	Zone Open	1 130	Za	Burg	Zone Alarm

Improved Trouble Audibles Programming

With Version 711, the Wireless Audible setting in **System Options** has been renamed to Trouble Audible. All system trouble audibles now follow this setting. Zone troubles do not follow this setting.

Panel Enhancements

Enhanced User Code Security

With Version 711 firmware, a keypad tamper message will be generated and sent to the central station as a result of three invalid code attempts. When an authorized user performs a sensor reset from the user menu, the tamper message is cleared from the status list and a restore report is sent to the central station. If a sensor reset is performed via the shortcut key, the tamper is not restored and a message is not sent to the central station.

Obtaining the New Firmware

XT International Series firmware updates are available, free of charge, on Dealer Admin (dealer.securecomwireless.com) or DMP.com/Dealer_Direct.