

Version 202 Update

Version 202 (8/17/20) firmware is now available on Dealer Admin (dealer.securecomwireless.com) or for download at DMP.com/Dealer_Direct.

Effective September 14th, 2020, all XT Series Panels are being manufactured with Version 202 firmware.

Panel Features

Door Device Type

Previously, when a door type device was attached to an XT Series panel, it could not be viewed or controlled from the Virtual Keypad™ App. Version 202 has added a new Door Device Type in **Device Setup**. If **DOOR** is selected, the device is displayed and able to be controlled in the Virtual Keypad App. This includes 734 and 1134 Access Control Modules. The Door Device Type is available on addresses 2-8 of XT Series panels.

7463 Network Keypad Support

With XT Series Version 202, a new device communication type has been added in **Device Setup** to support the 7463 Network Keypad. XT Series panels are able to support 7 network keypads on addresses 2-8 when the panel is connected via Ethernet, and one network keypad when the panel is connected over Wi-Fi. Network Keypads must be updated to Version 101 firmware in order to communicate with XT Series panels.

Removal of Messaging Setup

With XT Series Version 202, Messaging Setup has been removed from panel programming and is no longer supported. For your customers that would like to continue to receive SMS messages for panel events, they are able to:

1. Sign in to VirtualKeypad.com.
2. Select the **Notifications** tab. Here you can select existing notifications or create new notifications.
3. Select the **Recipients** tab. This will let you choose whether to receive notifications through push, text, or email.

Panel Enhancements

263LTE-FIRSTNET Support

XT Series Version 202 supports the upcoming 263LTE-FIRSTNET Cellular Communicator that operates on the AT&T FirstNet broadband network.

PIR Walk Test Remote Command

With XT Series 202, you can now initiate a PIR Walk Test remotely from Dealer Admin or the Tech APP. This test works similarly to the Wireless Walk Test and Standard Walk Test. The PIR needs to be tripped in order to test properly. The PIR LED will flash each time motion is detected for up to 30 minutes.

Easy Wi-Fi Password Programming

If the panel detects that the Wi-Fi password is incorrect, the keypad will display a message telling the user that they need to change the password. The keypad then walks the user through the steps for changing the password.

Improved Weather Accuracy

When the panel receives a weather update, it will compare the zip code in the weather string against the zip code it has in programming. If the zip codes match, the panel will update the weather. If the zip codes do not match, the panel will ignore the weather string. This ensures the panel is always providing the user with accurate weather information.

Supporting Software Updates

- **Dealer Admin Version 2.51** - Supports Door Device Type, Network Device Type, PIR Walk Test, and Wi-Fi programming.
- **Tech APP 2.11** - Supports Door Device Type and Network Device Type.
- **Virtual Keypad iOS and Android 6.32** - Supports Door Device Type.

Obtaining the New Firmware

XT Series firmware updates are available, free of charge, on Dealer Admin (dealer.securecomwireless.com) or DMP.com/Dealer_Direct.